



- Accommodates up to 16 x C1 type converter cards
- Dual Power Supplies
- Hot swappable converters and power supplies
- Operating temperature from -10°C to $+60^{\circ}\text{C}$
- Fits standard 19" Rack and occupies only 2U height

INTRODUCTION

The RM-C1 Rack Mount Chassis is designed for convenient mount of C1 type converter cards. Up to 16 such converters can be installed in this, only 2 units height in 19" rack occupying chassis. Hot swappable converters and power supplies for quick converters mount or power supplies replacements. Dual power supplies provides stable and uninterruptible operation for 24/7 in temperatures up to $+60^{\circ}\text{C}$.

SPECIFICATIONS

Model	RM-C1
Models of compatible converter cards	MCF-C1-xyz, MCG-C1-xyz
Max number of converter cards	16
Operating Temperature	$-10^{\circ}\text{C} \sim +60^{\circ}\text{C}$
Storage Temperature	$-40^{\circ}\text{C} \sim +85^{\circ}\text{C}$
Relative Humidity	0 ~ 90% non-condensing
Power input	Single, 110~240VAC
Number of installed power supplies	2
Max total power consumption	42W
Dimensions (H * D * W)	90 * 340 * 482mm (with mount ears and handles)
Weight	6.5kg
Mounting	19" Rack Mountable, 2U height
Standards	CE, FCC, RoHS

